

THE INVARIANT POLYNOMIAL ASSIGNMENT PROBLEM FOR LINEAR PERIODIC DISCRETE-TIME SYSTEMS¹

LEOPOLDO JETTO AND SAURO LONGHI

This paper considers the problem of assigning the closed loop invariant polynomials of a feedback control system, where the plant is a linear, discrete-time, periodic system. By a matrix algebraic approach, necessary and sufficient conditions for problem solvability are established and a parameterization of all periodic output controllers assigning the desired invariant polynomials is given.

1. INTRODUCTION

Various classes of processes, such as periodically time-varying networks and filters (for example switched-capacitors circuits and multirate digital filters), chemical processes, multirate sampled-data systems, can be modeled through a linear periodic system (see, e. g., [2, 13] and references therein). Moreover, the study of linear periodic systems can be helpful even for the stabilization and control of time-invariant linear systems through a periodic controller [1, 8, 18, 19, 21, 27], and for the stabilization and control of a class of bilinear systems [10, 11, 12].

In the discrete-time case, a control theory is developing with the help of algebraic and geometric techniques and contributions on several control problem have been given, including eigenvalue assignment, state and output dead-beat control, disturbance decoupling, model matching, adaptive control, robust control and optimal H_2/H_∞ control (see, e. g., [3, 5, 7, 13, 15, 17, 22, 25, 26]).

The aim of this paper is to analyze the invariant polynomial assignment problem for the class of discrete-time linear periodic systems. This problem generalizes the characteristic polynomial assignment, which, for the same class of systems, was solved by a geometric approach in [5, 15, 17, 22]. For time-invariant plants, the invariant polynomial assignment was considered in [19, 20, 23, 27].

The paper is organized in the following way. In Section 2 preliminary definitions and results are given. The problem considered in this paper is formally stated in Section 3, and conditions for its solvability are constructively established in Section 4.

¹Work supported by the Ministero dell'Università e della Ricerca Scientifica.

2. PRELIMINARY RESULTS

Consider the ω -periodic discrete-time system Σ described by

$$\begin{aligned} x(k+1) &= A(k)x(k) + B(k)u(k), & (1) \\ y(k) &= C(k)x(k), & (2) \end{aligned}$$

where $k \in \mathbb{Z}$, $x(k) \in \mathbb{R}^n$ is the state, $u(k) \in \mathbb{R}^p$ is the input, $y(k) \in \mathbb{R}^q$ is the output and $A(\cdot), B(\cdot), C(\cdot)$ are periodic matrices of period ω (briefly, ω -periodic). Denote also by $\Phi(k, k_0)$, $k \geq k_0$, the transition matrix associated with $A(\cdot)$.

It is well-known that, for any initial time $k_0 \in \mathbb{Z}$, the output response of system Σ for $k \geq k_0$, to given initial state $x(k_0)$ and control function $u(\cdot)$, can be obtained through the time-invariant associated system of Σ at time k_0 , denoted by $\Sigma^a(k_0)$ [24]. $\Sigma^a(k)$ is represented by

$$x_k(h+1) = E_k x_k(h) + J_k u_k(h) \tag{3}$$

$$y_k(h) = L_k x_k(h) + M_k u_k(h) \tag{4}$$

where $E_k := \Phi(\omega+k, k)$, $J_k := [(J_k)_1 \cdots (J_k)_\omega]$, $(J_k)_i := \Phi(\omega+k, i+k)B(i-1+k)$, $i = 1, \dots, \omega$, $L_k := [(L_k)'_1 \cdots (L_k)'_\omega]'$, $(L_k)_i := C(i-1+k)\Phi(i-1+k, k)$, $i = 1, \dots, \omega$, $M_k := [(M_k)_{ij} \in \mathbb{R}^{q \times p}$, $i, j = 1, \dots, \omega]$, with $(M_k)_{ij} := C(i-1+k)\Phi(i-1+k, j+k)B(j-1+k)$, if $i > j$, and $(M_k)_{ij} := 0$, if $i \leq j$.

In fact, if $x_k(0) = x(k)$ and $u_k(h) := [u'(h\omega+k) \ u'(h\omega+k+1) \ \cdots \ u'(h\omega+k+\omega-1)]'$ for all $h \in \mathbb{Z}^+$, then $x_k(h) = x(k+h\omega)$ and $y_k(h) = [y'(h\omega+k) \ y'(h\omega+k+1) \ \cdots \ y'(h\omega+k+\omega-1)]'$ for all $h \in \mathbb{Z}^+$. The notion of associated system at time k allows one to analyze structural and stability properties and pole-zero-structures of periodic systems [2, 4, 14]. For example, the subspace of reachable (unobservable) states of system Σ at time k is readily seen to coincide with that of system $\Sigma^a(k)$ if it is expressed in terms of matrices E_k, J_k, L_k and M_k [14]. Obviously, $\Sigma^a(k+\omega) = \Sigma^a(k)$ for all integer k . A simple test for the reachability (observability) of system Σ at time k was also introduced in [16] making use of the following block-diagonal matrices:

$$\mathcal{A}_k := \text{blockdiag}\{A(k), A(k+1), \dots, A(\omega-1+k)\}, \tag{5}$$

$$\mathcal{B}_k := \text{blockdiag}\{B(k), B(k+1), \dots, B(\omega-1+k)\}, \tag{6}$$

$$\mathcal{C}_k := \text{blockdiag}\{C(k), C(k+1), \dots, C(\omega-1+k)\}, \tag{7}$$

$$\mathcal{R}_k(\lambda) := \begin{bmatrix} 0 & I_{(\omega-1)n} \\ \lambda I_n & 0 \end{bmatrix}, \quad \lambda \in \mathbb{C}, \tag{8}$$

where I_n denotes the identity matrix of dimension n .

Lemma 2.1. [16] System Σ is reachable (observable) at time k if and only if the following matrix

$$[\mathcal{A}_k - \mathcal{R}_k(\lambda) \quad \mathcal{B}_k] \quad ([\mathcal{A}'_k - \mathcal{R}'_k(\lambda) \quad \mathcal{B}'_k])'$$

has full row-rank (column-rank) for all $\lambda \in \mathbb{C}$, or equivalently for all the eigenvalues of E_k .

The notions of invariant zero, transmission zero and pole of the ω -periodic system Σ at time k are defined with reference to the following $\omega q \times \omega p$ matrix

$$W_k(d) = L_k d(I_n - dE_k)^{-1} J_k + M_k, \tag{9}$$

where $d := z^{-1}$ is the backward shift operator. The rational matrix $W_k(d)$ is the transfer matrix of the associated system of Σ at time k and is called the *associated transfer matrix of Σ at time k* . A complete analysis of pole-zero structure of system Σ is reported in [14] and [16] making use of the associated transfer matrix characterized with the forward shift operator z . The following result, that follows from Lemma 2.1 in [14], shows the dependence of $W_k(d)$ with respect to the initial time k .

Lemma 2.2. For any integer k it holds that:

$$W_{k+1}(d) = \begin{bmatrix} 0 & I_{q(\omega-1)} \\ d^{-1}I_q & 0 \end{bmatrix} W_k(d) \begin{bmatrix} 0 & dI_p \\ I_{p(\omega-1)} & 0 \end{bmatrix}. \tag{10}$$

As a consequence of this result the rank m of $W_k(d)$ is independent of time k (see, e. g., [14] for a similar result with the forward shift operator z).

The transfer matrix $W_k(d)$ can be factored as

$$W_k(d) = A_k^{-1}(d) B_k(d) = \overline{B}_k(d) \overline{A}_k^{-1}(d), \tag{11}$$

where $A_k(d)$ and $B_k(d)$ are relatively left prime (*rlp*) polynomial matrices and $\overline{A}_k(d)$ and $\overline{B}_k(d)$ are relatively right prime (*rrp*) polynomial matrices.

Analogously to the time-invariant case [23], the invariant polynomials of $I_n - dE_k$ are called the *invariant polynomials of Σ at time k* . As shown in [14, 16], the product of these polynomials characterizes the stability properties of Σ .

Under the hypothesis of reachability and observability of Σ at time k , the invariant polynomials of Σ at time k are associate of the invariant polynomials of the Smith forms of $A_k(d)$ and $\overline{A}_k(d)$ [23].

Denote by $\chi(q, p, \omega)$ the class of $\omega q \times \omega p$ rational matrices

$$W(d) = \begin{bmatrix} W_{11}(d) & W_{12}(d) & \cdots & W_{1\omega}(d) \\ W_{21}(d) & W_{22}(d) & \cdots & W_{2\omega}(d) \\ \vdots & \vdots & \ddots & \vdots \\ W_{\omega 1}(d) & W_{\omega 2}(d) & \cdots & W_{\omega\omega}(d) \end{bmatrix}, \quad W_{ij}(d) \in \mathbb{C}^{q \times p}, \quad i, j = 1, \dots, \omega, \tag{12}$$

with $W_{ij}(0) = 0, i < j, i, j = 1, \dots, \omega$. The class $\chi(q, p, \omega)$ characterizes the transfer matrices of ω -periodic systems. In fact, the causality of ω -periodic system Σ implies that the associated transfer matrix of Σ at time k belongs to the class $\chi(q, p, \omega)$ for all $k \in \mathbb{Z}$ [6]. Then, the causality of Σ implies that the roots of the invariant polynomials of Σ at time k are different from zero for all integers k . This in turn implies that matrices $A_k(0)$ and $\overline{A}_k(0)$ are nonsingular. Foregoing considerations and Lemma 2.2 allow us to prove the following result.

Lemma 2.3. The invariant polynomials of Σ at time k are independent of k .

Remark 2.1. The choice of the backward shift operator $d = z^{-1}$ allowed us to prove the independence of pole structure of Σ of time k . The same result does not hold if the forward operator z is used [16]. In particular in [14] it is shown that the structure of null poles may depend on k .

Moreover, $\chi(q, p, \omega)$ characterizes also the class of rational matrices that can be realized by an ω -periodic system of the form (1), (2). The solution of the minimal realization problem for the periodic case is described by a system reachable and observable at any time whose matrices have generally time-varying dimensions. In general, the subspaces of reachable states and/or observable states may have time-varying dimensions. Therefore, it is natural, in order to consistently solve the minimal realization problem, to allow for state-space description having time-varying dimensions. The possibility of computing a “quasi” minimal (reachable and observable at least in one time) uniform (fixed-dimension) realization is also available. Efficient algorithms for the computation of minimal or quasi minimal realization of a given transfer matrix are introduced in [6] and [9].

Remark 2.2 Note that, given a transfer matrix $H(d) = D^{-1}(d) N(d) = \overline{N}(d) \overline{D}^{-1}(d) \in \mathbb{C}^{q\omega \times p\omega}$ with $D(d)$ and $N(d)$ *rlp* polynomial matrices and $\overline{D}(d)$ and $\overline{N}(d)$ *rrp* polynomial matrices and both $D(0)$ and $\overline{D}(0)$ non singular, then a sufficient condition for $H(d)$ belong to the class $\chi(q, p, \omega)$ is that $N(0) = 0$ and $\overline{N}(0) = 0$.

3. CONTROL SYSTEM STRUCTURE AND PROBLEM STATEMENT

Assume that system Σ is minimal (reachable and observable at all times), and consider an ω -periodic minimal controller Σ_G for system Σ acting in the feedback control structure of Figure 1 and described by

$$x_G(k+1) = A_G(k) x_G(k) + B_G(k) e_2(k), \quad (13)$$

$$y_2(k) = C_G(k) x_G(k) + D_G(k) e_2(k), \quad (14)$$

where $x_G(k) \in \mathbb{R}^{n_G(k)}$ is the state, with $n_G(k+\omega) = n_G(k)$, and

$$e_1(k) := u_1(k) - y_2(k), \quad (15)$$

$$e_2(k) := u_2(k) + y_1(k), \quad (16)$$

with $y_1(k) = y(k)$ (the output of Σ), $e_1(k) = u(k)$ (the input of Σ) and $u_1(k)$ and $u_2(k)$ external inputs.

The $\omega p \times \omega q$ associated transfer matrix of Σ_G at time k is expressed by

$$W_k^G(d) = L_k^G d(I_{n_G(k)} - dE_k^G)^{-1} J_k^G + M_k^G, \quad (17)$$

where matrices $L_k^G \in \mathbb{R}^{\omega p \times n_G(k)}$, $E_k^G \in \mathbb{R}^{n_G(k) \times n_G(k)}$, $J_k^G \in \mathbb{R}^{n_G(k) \times \omega q}$ and $M_k^G \in \mathbb{R}^{\omega p \times \omega q}$ are defined as matrices L_k , E_k , J_k and M_k with matrices $A(\cdot)$, $B(\cdot)$ and

$C(\cdot)$ substituted by matrices $A_G(\cdot)$, $B_G(\cdot)$, $C_G(\cdot)$ respectively and with $(M_k^G)_{ii} = D_G(i - 1 + k)$, $i = 1, \dots, \omega$.

Fig. 1. The feedback control structure.

Causality of system Σ_G implies that $W_k^G(d)$ belongs to the class $\chi(p, q, \omega)$.
Let $W_k^G(d)$ be factored as

$$W_k^G(d) = P_k^{-1}(d) Q_k(d) = \bar{Q}_k(d) \bar{P}_k^{-1}(d) \quad (18)$$

where $P_k(d)$ and $Q_k(d)$ are rlp polynomial matrices and $\bar{P}_k(d)$ and $\bar{Q}_k(d)$ are rrp polynomial matrices. The problem considered in this paper is formally stated as follows.

Problem 3.1. Given an ω -periodic system Σ reachable and observable at all times, and m causal polynomials $s_1(d)$, $s_2(d)$, \dots , $s_m(d)$ such that $s_{i+1}(d)$ divides $s_i(d)$, find a minimally realized ω -periodic controller Σ_G described by (13), (14) and acting in the feedback system of Figure 1, such that the closed loop system Σ_{fb} be minimally realized and its invariant polynomials be associated of $s_i(d)$, $i = 1, 2, \dots, m$.

4. PROBLEM SOLUTION

Denote by Σ_{fb} the ω -periodic system reported in Figure 1 and described by (1), (2), (13), (14), (15) and (16) with input $u(k)$ and output $y(k)$ of Σ equal to $e_1(k)$ and $y_1(k)$, respectively.

Define:

$$v(k) := [u_1'(k) \quad u_2'(k)]', \quad w_1(k) := [y_1'(k) \quad e_1'(k)]', \quad w_2(k) := [y_2'(k) \quad e_2'(k)]', \quad (19)$$

the ω -periodic feedback system Σ_{fb} is described by the following equations:

$$\begin{aligned} \begin{bmatrix} x(k+1) \\ x_G(k+1) \end{bmatrix} &= \begin{bmatrix} A(k) - B(k)D_G(k)C(k) & -B(k)C_G(k) \\ B_G(k)C(k) & A_G(k) \end{bmatrix} \begin{bmatrix} x(k) \\ x_G(k) \end{bmatrix} \\ &+ \begin{bmatrix} B(k) & -B(k)D_G(k) \\ 0 & B_G(k) \end{bmatrix} v(k), \end{aligned} \quad (20)$$

$$w_1(k) = \begin{bmatrix} C(k) & 0 \\ -D_G(k)C(k) & -C_G(k) \end{bmatrix} \begin{bmatrix} x(k) \\ x_G(k) \end{bmatrix} + \begin{bmatrix} 0 & 0 \\ I & -D_G(k) \end{bmatrix} v(k), \quad (21)$$

$$w_2(k) = \begin{bmatrix} D_G(k)C(k) & C_G(k) \\ C(k) & 0 \end{bmatrix} \begin{bmatrix} x(k) \\ x_G(k) \end{bmatrix} + \begin{bmatrix} 0 & D_G(k) \\ 0 & I \end{bmatrix} v(k). \quad (22)$$

Denote with $W_k^1(d)$ and $W_k^2(d)$ the associated transfer matrices at time k of the ω -periodic feedback system Σ_{fb} relating input $v(\cdot)$ with outputs $w_1(\cdot)$ and $w_2(\cdot)$, respectively.

Introducing the lifted representations of inputs and outputs of Σ_{fb} :

$$u_k^1(h) := [u'_1(k+h\omega) u'_1(k+1+h\omega) \cdots u'_1(k+\omega-1+h\omega)]', \quad (23)$$

$$u_k^2(h) := [u'_2(k+h\omega) u'_2(k+1+h\omega) \cdots u'_2(k+\omega-1+h\omega)]', \quad (24)$$

$$v_k(h) := [v'(k+h\omega) v'(k+1+h\omega) \cdots v'(k+\omega-1+h\omega)]', \quad (25)$$

$$y_k^1(h) := [y'_1(k+h\omega) y'_1(k+1+h\omega) \cdots y'_1(k+\omega-1+h\omega)]', \quad (26)$$

$$e_k^1(h) := [e'_1(k+h\omega) e'_1(k+1+h\omega) \cdots e'_1(k+\omega-1+h\omega)]', \quad (27)$$

$$w_k^1(h) := [w'_1(k+h\omega) w'_1(k+1+h\omega) \cdots w'_1(k+\omega-1+h\omega)]', \quad (28)$$

$$y_k^2(h) := [y'_2(k+h\omega) y'_2(k+1+h\omega) \cdots y'_2(k+\omega-1+h\omega)]', \quad (29)$$

$$e_k^2(h) := [e'_2(k+h\omega) e'_2(k+1+h\omega) \cdots e'_2(k+\omega-1+h\omega)]', \quad (30)$$

$$w_k^2(h) := [w'_2(k+h\omega) w'_2(k+1+h\omega) \cdots w'_2(k+\omega-1+h\omega)]'. \quad (31)$$

it can be verified the existence of appropriate unimodular matrices U_a and U_b such that the following relations are satisfied:

$$\begin{bmatrix} u_k^1(h) \\ u_k^2(h) \end{bmatrix} = U_a v_k(h), \quad (32)$$

$$\begin{bmatrix} y_k^1(h) \\ e_k^1(h) \end{bmatrix} = U_b w_k^1(h), \quad (33)$$

$$\begin{bmatrix} y_k^2(h) \\ e_k^2(h) \end{bmatrix} = U_a w_k^2(h). \quad (34)$$

Then, the associated transfer matrices $W_k^1(d)$ and $W_k^2(d)$ of Σ_{fb} at time k satisfy the following relations:

$$W_k^1(d) = U_b^{-1} \begin{bmatrix} W_k^{y_1 u_1}(d) & W_k^{y_1 u_2}(d) \\ W_k^{e_1 u_1}(d) & W_k^{e_1 u_2}(d) \end{bmatrix} U_a, \quad (35)$$

$$W_k^2(d) = U_a^{-1} \begin{bmatrix} W_k^{y_2 u_1}(d) & W_k^{y_2 u_2}(d) \\ W_k^{e_2 u_1}(d) & W_k^{e_2 u_2}(d) \end{bmatrix} U_a, \quad (36)$$

where $W_k^{y_i u_j}(d)$ and $W_k^{e_i u_j}(d)$ denote the associated transfer matrices at time k of the ω -periodic feedback system Σ_{fb} relating input $u_j(\cdot)$, $j = 1, 2$ with output $y_i(\cdot)$, $e_i(\cdot)$ $i = 1, 2$, respectively.

Denoting as

$$F_k^1(d) = P_k(d) \bar{A}_k(d) + Q_k(d) \bar{B}_k(d), \quad (37)$$

$$F_k^2(d) = A_k(d) \bar{P}_k(d) + B_k(d) \bar{Q}_k(d), \quad (38)$$

and arguing as in [23] it can be shown that

$$W_k^1(d) = U_b^{-1} \begin{bmatrix} \overline{B}_k(d) \\ \overline{A}_k(d) \end{bmatrix} (F_k^1(d))^{-1} [P_k(d) \quad -Q_k(d)] U_a, \tag{39}$$

$$W_k^2(d) = U_a^{-1} \begin{bmatrix} -\overline{Q}_k(d) \\ \overline{P}_k(d) \end{bmatrix} (F_k^2(d))^{-1} [B_k(d) \quad A_k(d)] U_a. \tag{40}$$

We are now in a position to prove the following main theorem.

Theorem 4.1 Problem 3.1 admits a solution if and only if $m \leq \min(\omega p, \omega q)$.

Proof. Necessity. Under the hypothesis on reachability and observability at all times of the ω -periodic systems Σ and Σ_G , by Lemma 2.1 applied to Σ_{fb} it can be shown that the ω -periodic system Σ_{fb} is reachable at all times and observable through the outputs $w_1(\cdot)$ and $w_2(\cdot)$ at all times. Then (20) and (21) constitute a minimal realization of transfer matrix $W_k^1(d)$ and (20) and (22) constitute a minimal realization of transfer matrix $W_k^2(d)$. Moreover, for each time k , the nonunit invariant polynomials of the $(\omega p \times \omega p)$ polynomial matrix $F_k^1(d)$ are associated of the nonunit invariant polynomials of the $(\omega q \times \omega q)$ polynomial matrix $F_k^2(d)$ and both are associated of the nonunit invariant polynomials at time k of the ω -periodic feedback system Σ_{fb} [23]. This implies that the number m of the invariant polynomials at time k of the ω -periodic feedback system Σ_{fb} can not be larger than $m \leq \min(\omega p, \omega q)$.

Sufficiency. As $A_k(d)$ and $B_k(d)$ are rlp and $\overline{A}_k(d)$ and $\overline{B}_k(d)$ are rrp , equations (37) and (38) can be solved for arbitrary $F_k^1(d)$ and $F_k^2(d)$. Hence, if $m \leq \min(\omega p, \omega q)$, the $s_i(d), i = 1, \dots, m$ can be assigned to Σ_{fb} as invariant polynomials choosing $F_k^1(d)$ and $F_k^2(d)$ as polynomial matrices whose nonunit invariant polynomial are associate (two polynomials are called associate if their ratio is a scalar [23]) of the $s_i(d), i = 1, \dots, m$ and then to solve (37) or (38) with respect to the pairs $(P_k(d), Q_k(d))$ or $(\overline{P}_k(d), \overline{Q}_k(d))$ respectively. Moreover, as the invariant polynomials of Σ_{fb} are independent of k , the solutions of (37) and (38) can be found for arbitrary k .

For an arbitrary integer k , all the solutions $P_k(d)$ and $Q_k(d)$ of (37) are given by

$$\begin{bmatrix} P_k(d) & Q_k(d) \end{bmatrix} = \begin{bmatrix} F_k^1(d) & T_k(d) \end{bmatrix} U_k(d) \tag{41}$$

where $U_k(d)$ is the unimodular matrix given by

$$U_k(d) = \begin{bmatrix} G_k(d) & H_k(d) \\ -B_k(d) & A_k(d) \end{bmatrix},$$

$G_k(d)$ and $H_k(d)$ are polynomial matrices such that

$$G_k(d)\overline{A}_k(d) + H_k(d)\overline{B}_k(d) = I_{\omega p},$$

and $T_k(d)$ is an arbitrary polynomial matrix. For the solution (41) be adequate for Problem 3.1, $T_k(d)$ must be such that

$$4a) \quad P_k(d) \text{ and } Q_k(d) \text{ are } rlp, \quad 4b) \quad P_k^{-1}(d) Q_k(d) \in \chi(p, q, \omega).$$

Analogously, for an arbitrary integer k , all the solutions of (38) are given by

$$\begin{bmatrix} \overline{P}_k(d) \\ \overline{Q}_k(d) \end{bmatrix} = \overline{U}_k(d) \begin{bmatrix} F_k^2(d) \\ \overline{T}_k(d) \end{bmatrix}, \tag{42}$$

where $\overline{U}_k(d)$ is the unimodular matrix given by

$$\overline{U}_k(d) = \begin{bmatrix} \overline{G}_k(d) & -\overline{B}_k(d) \\ \overline{H}_k(d) & \overline{A}_k(d) \end{bmatrix},$$

$\overline{G}_k(d)$ and $\overline{H}_k(d)$ are polynomial matrices such that

$$A_k(d) \overline{G}_k(d) + B_k(d) \overline{H}_k(d) = I_{\omega q},$$

and $\overline{T}_k(d)$ is an arbitrary polynomial matrix. For the solution (42) be adequate to Problem 3.1, $\overline{T}_k(d)$ must be such that:

$$4\bar{a}) \quad \overline{P}_k(d) \text{ and } \overline{Q}_k(d) \text{ are } rrp, \quad 4\bar{b}) \quad \overline{Q}_k(d) \overline{P}_k(d)^{-1} \in \chi(p, q, \omega).$$

It remains to show that matrices and $T_k(d)$ and $\overline{T}_k(d)$ such that the pairs $(P_k(d), Q_k(d))$ and $(\overline{P}_k(d), \overline{Q}_k(d))$ satisfy properties 4a, 4b and 4 \bar{a} , 4 \bar{b} respectively, can always be found.

With reference to solutions (42), matrix $\overline{T}_k(d)$ can be found as follows. By the causality of Σ , $A_k(0)$ is non singular, so that left primeness of $A_k(d)$ and $B_k(d)$ implies left primeness of $A_k(d)$ and $dB_k(d)$. This in turn implies that the equation

$$A_k(d) \overline{P}_k^a(d) + dB_k(d) \overline{Q}_k^a(d) = F_k^2(d), \tag{43}$$

can be solved with respect to $\overline{P}_k^a(d)$ and $\overline{Q}_k^a(d)$ for any $F_k^2(d)$. For an arbitrary integer k the general solution of (43) is

$$\begin{bmatrix} \overline{P}_k^a(d) \\ \overline{Q}_k^a(d) \end{bmatrix} = \overline{U}_k^a(d) \begin{bmatrix} F_k^2(d) \\ \overline{T}_k^a(d) \end{bmatrix}, \tag{44}$$

where $\overline{U}_k^a(d)$ is a unimodular matrix given by

$$\overline{U}_k^a(d) = \begin{bmatrix} \overline{G}_k^a(d) & -d\overline{B}_k(d) \\ \overline{H}_k^a(d) & \overline{A}_k(d) \end{bmatrix}$$

$\overline{G}_k^a(d)$ and $\overline{H}_k^a(d)$ are polynomial matrices satisfying

$$A_k(d) \overline{G}_k^a(d) + dB_k(d) \overline{H}_k^a(d) = I_{\omega q}, \tag{45}$$

and $\overline{T}_k^a(d)$ is an arbitrary polynomial matrix. The unimodularity of $\overline{U}_k^a(d)$ implies that if $\overline{T}_k^a(d)$ is chosen right coprime with $F_k^2(d)$, also $\overline{P}_k^a(d)$ and $\overline{Q}_k^a(d)$ are right coprime. Taking into account that by the causality of Σ_{fb} and (43), $\overline{P}_k^a(0)$ is nonsingular, one has that also $\overline{P}_k^a(d)$ and $d\overline{Q}_k^a(d)$ are right coprime, so that by

putting $\bar{G}_k(d) = \bar{G}_k^a(d), \bar{H}_k(d) = d\bar{H}_k^a(d), \bar{T}_k(d) = d\bar{T}_k^a(d)$ one has that the pair $(\bar{P}_k(d), \bar{Q}_k(d))$ given by

$$\bar{P}_k(d) = \bar{P}_k^a(d) = \bar{G}_k(d) F_k^2(d) - \bar{B}_k(d) \bar{T}_k(d), \tag{46}$$

$$\bar{Q}_k(d) = d\bar{Q}_k^a(d) = \bar{H}_k(d) F_k^2(d) + \bar{A}_k(d) \bar{T}_k(d), \tag{47}$$

defines a class of solutions (42) satisfying 4 \bar{a} and 4 \bar{b} (see Remark 2.2).

By arguing in a similar way, one has that the pair

$$P_k(d) = F_k^1(d) G_k(d) - T_k(d) B_k(d), \tag{48}$$

$$Q_k(d) = F_k^1(d) H_k(d) + T_k(d) A_k(d), \tag{49}$$

where $G_k(d) = G_k^a(d), H_k(d) = dH_k^a(d)$ with $G_k^a(d)$ and $H_k^a(d)$ such that

$$G_k^a(d) \bar{A}_k(d) + H_k^a(d) d\bar{B}_k(d) = I_{\omega p},$$

and where $T_k(d) = dT_k^a(d), T_k^a(d)$ being any polynomial matrix left prime with $F_k^1(d)$, defines a class of solutions of (37) satisfying 4a and 4b (see Remark 2.2). Hence, under the assumption $m \leq \min(\omega p, \omega q)$, the existence of solutions of Problem 3.1 has been constructively established. \square

5. CONCLUSIONS

In this paper the pole placement problem for linear discrete-time periodic systems has been considered. This problem has been formulated in the more general context of the invariant polynomial assignment, whence pole placement follows as a particular case. Necessary and sufficient conditions for problem solvability have been given in Theorem 3.1. The sufficiency proof of this theorem gives a parameterization of all controllers solving the problem in terms of causal transfer matrices that are minimally realizable with a periodic state-space representation. The proof has been performed in two steps. First, the set of all admissible solutions has been formally defined, then a procedure to effectively construct an admissible solution has been provided.

(Received February 14, 1996.)

REFERENCES

[1] B. D. O. Anderson and J. B. Moore: Decentralized control using time-varying feedback. In: Control and Dynamic Systems, Vol. 22 (C. T. Leondes, ed.), Academic Press, London 1985, pp. 85-115.

[2] S. Bittanti: Deterministic and stochastic linear periodic systems. In: Time Series and Linear Systems (S. Bittanti, ed.), Springer-Verlag, Berlin 1986.

[3] S. Bittanti, P. Colaneri and G. De Nicolao: The difference periodic Riccati equation for the periodic prediction problem. IEEE Trans. Automat. Control AC-33 (1988), 706.

[4] P. Bolzern, P. Colaneri and R. Scattolini: Zeros of discrete-time linear periodic systems. IEEE Trans. Automat. Control AC-31 (1986), 1057.

- [5] P. Colaneri: Output stabilization via pole-placement of discrete-time linear periodic systems. *IEEE Automat. Control AC-36* (1991), 739.
- [6] P. Colaneri and S. Longhi: The realization problem for linear periodic systems. *Automatica* *31* (1995), 5, 775–779.
- [7] M. A. Dahleh, P. G. Voulgaris and L. S. Valavani: Optimal and robust controllers for periodic and multirate systems. *IEEE Trans. Automat. Control AC-37* (1992), 1, 90–99.
- [8] J. H. Davis: Stability conditions derived from spectral theory: discrete systems with periodic feedback. *SIAM J. Control* *10* (1972), 1, 1–13.
- [9] I. Gohberg, M. A. Kaashoek and L. Lerer: Minimality and realization of discrete time-varying systems. *Oper. Theory: Adv. Appl.* *56* (1992), 261–296.
- [10] O. M. Grasselli, A. Isidori and F. Nicolò: Output regulation of a class of bilinear systems under constant disturbances. *Automatica* *15* (1979), 189–195.
- [11] O. M. Grasselli, A. Isidori and F. Nicolò: Dead-beat control of discrete-time bilinear systems. *Internat. J. Control* *32* (1980), 1, 31–39.
- [12] O. M. Grasselli and S. Longhi: On the stabilization of a class of bilinear systems. *Internat. J. Control* *37* (1983), 2, 413–420.
- [13] O. M. Grasselli and S. Longhi: Disturbance localization by measurements feedback for linear periodic discrete-time systems. *Automatica* *24* (1988), 375–385.
- [14] O. M. Grasselli and S. Longhi: Zeros and poles of linear periodic discrete-time systems. *Circuits Systems Signal Process.* *7* (1988), 361–380.
- [15] O. M. Grasselli and S. Longhi: Pole-placement for nonreachable periodic discrete-time systems. *Math. Control Signals Systems* *4* (1991), 439–455.
- [16] O. M. Grasselli and S. Longhi: Finite zero structure of linear periodic discrete-time systems. *Internat. J. Systems Sci.* *22* (1991), 1785–1806.
- [17] V. Hernandez and A. Urbano: Pole-placement problem for discrete-time linear periodic systems. *Internat. J. Control* *50* (1989), 361–371.
- [18] T. Kaczorek: Pole placement for linear discrete-time systems by periodic output-feedback. *Systems Control Lett.* *6* (1985), 267–269.
- [19] T. Kaczorek: Invariant factors and pole/variant zero assignments by periodic output-feedback for multivariable systems. In: *Preprints of the 10th IFAC Congress, Munich 1987, Vol. 9, pp. 138–143.*
- [20] T. Kaczorek: *Linear Control Systems, Volume 2.* Research Studies Press LTD, Taunton 1993.
- [21] P. P. Khargonekar, K. Poolla and A. Tannenbaum: Robust control of linear time-invariant plants using periodic compensators. *IEEE Trans. Automat. Control AC-30* (1985), 1088.
- [22] M. Kono: Eigenvalue assignment in linear periodic discrete-time systems. *Internat. J. Control* *32* (1980), 1, 149–158.
- [23] V. Kučera: *Discrete Linear Control – The Polynomial Equation Approach.* J. Wiley & Sons, Chichester 1979.
- [24] R. A. Mayer and C. S. Burrus: A unified analysis of multirate and periodically time-varying digital filters. *IEEE Trans. Circuits and Systems CSA-22* (1975), 162–168.
- [25] F. Ohkawa: Model reference adaptive control system for discrete linear time-varying systems with periodically varying parameters and time delay. *Internat. J. Control* *44* (1986), 171–179.
- [26] B. Park and E. I. Verriest: Canonical forms on discrete linear periodically time-varying systems and a control application. In: *Proc. of the 28th IEEE Conf. on Decision and Control, Tampa 1989, 1220–1225.*
- [27] J. L. Willems, V. Kučera and P. Brunovsky: On the assignment of invariant factors by time-varying feedback strategies. *Systems Control Lett.* *5* (1984), 75–80.

Prof. Dr. Leopoldo Jetto and Prof. Dr. Sauro Longhi, Dipartimento di Elettronica ed Automatica, Università degli Studi di Ancona, via Brezze Bianche, 60131 Ancona. Italy.